

TRANS-12VC et TRANS-24VC



SPECIFICATION

Power: 12 to 60 watts
 Voltage: 12 VDC ou 24 VDC
 Wall plug 120 VAC and DC connector output



To order

TRANS	-	12VC	-	12W
Transformer		12VC: 12 VDC		12W: 12 watts
		24VC: 24 VDC		24W: 24 watts
				36W: 36 watts
				48W: 48 watts
				60W: 60 watts

PRODUCT DIMENSIONS

Power	Length	Width	Height
12W	3 1/2" (89 mm)	1.97" (50 mm)	1 1/4" (32 mm)
24W	3 13/16" (96 mm)	1 7/8" (45 mm)	1 1/16" (28 mm)
36W	4 3/4" (120 mm)	2" (51 mm)	1 1/4" (32 mm)
48W	4 3/4" (120 mm)	2" (51 mm)	1 1/4" (32 mm)
60W	4 3/4" (120 mm)	2 1/8" (53 mm)	1 3/8" (33 mm)

INTENDED USE

Our TRANS-12VC or TRANS-24VC series transformers are perfect for powering our 12 VDC or 24 VDC luminaires. They are simple to install, as they plug directly into an electrical outlet.

Fitted with a male connector, they are compatible with our product connectors or CON-DC-FEM and FIL-CON-DC-FEM. They are recommended for residential installations.

CURRENT ENTREY AT 120 VAC

Product code	Ampere	Product code	Ampere
TRANS-12VC-12W	0,5	TRANS-24VC-12W	0,7
TRANS-12VC-24W	0,7	TRANS-24VC-24W	0,7
TRANS-12VC-36W	0,7	TRANS-24VC-36W	2,0
TRANS-12VC-48W	2,0	TRANS-24VC-48W	2,0
TRANS-12VC-60W	2,0	TRANS-24VC-60W	2,0

WARNING

1. Install this product in accordance with the applicable electrical code. This product is designed for installation by a qualified person or electrician.
2. This product is designed for indoor use and is not protected from moisture.
3. This product must be connected using the connectors built into the product.
4. This product may have an ignition delay of up to 2 seconds.

WARRANTY

This product is warranted against manufacturing defects for a period of one (1) year from the date of purchase and does not include the other products shown on this sheet, if any. For a complete description of the warranty, visit www.innovadel.com or contact our technical support. Any modification, alteration, improper installation of the product, or cutting of connectors, will void the warranty.